



- Pure sine wave inverter
- Selectable input voltage range for home appliances and personal computers
- Selectable charging current based on applications
- Configurable AC/Solar input priority via LCD setting
- Compatible to mains voltage or generator power
- Auto restart while AC is recovering
- Overload and short circuit protection
- Smart battery charger design for optimized battery performance
- Cold start function

NORDIC 1KVA/2KVA/3KVA/4KVA/5KVA Inverter/Charger Selection Guide

MODEL	NI-INV-1000-12-A	NI-INV-2000-24-A	NI-INV-3000-24-A	NI-INV-4000-48-A	NI-INV-5000-48-A
Rated Power	1000VA / 800W	2000VA/1600W	3000VA / 2400W	4000VA / 3200W	5000VA / 4000W
INPUT					
Voltage	230 VAC				
Selectable Voltage Range	170-280 VAC (For Personal Computers) 90-280 VAC (For Home Appliances)				
Frequency Range	50 Hz/60 Hz (Auto sensing)				
OUTPUT					
AC Voltage Regulation (Batt. Mode)	230VAC ± 15%				
Surge Power	2000VA	4000VA	6000VA	8000VA	10000VA
Efficiency (Peak)	90%	93%			
Transfer Time	10 ms (For Personal Computers) 20 ms (For Home Appliances)				
Waveform	Pure sine wave				
BATTERY					
Battery Voltage	12 VDC	24 VDC			48 VDC
Floating Charge Voltage	13.5 VDC	27 VDC			54 VDC
Overcharge Protection	15 VDC	30 VDC			60 VDC
Maximum Charge Current	10 A or 20 A	20 A or 30 A			20 A or 30 A
SOLAR CHARGER (OPTION)					
Charging Current	50A				
Maximum PV Array Open Circuit Voltage	125 VDC				
Standby Power Consumption	1 W	2 W			2W
PHYSICAL					
Dimension, D X W X H (mm)	95 x 250 x 330	100 x 272 x 367		110 x 300 x 455	
Net Weight (kgs)	5.0	6.35	6.85	7.5	8.5
OPERATING ENVIRONMENT					
Humidity	5% to 95% Relative Humidity(Non-condensing)				
Operating Temperature	0°C - 55°C				
Storage Temperature	-15°C - 60°C				

Product specifications are subject to change without further notice